

SHURFLO® LINEAR CURRENT BOOSTER PUMP CONTROLLERS

OPTIMIZE THE PERFORMANCE OF YOUR SOLAR SUBMERSIBLE PUMP

- SHURflo LCB pump controllers are high quality DC power converters designed to interface between a DC solar pump and DC power source like solar panels.
- Their main function is to maximize the daily output of water while providing protection for the pump.
- The solid state controller will protect the pump systems and give trouble-free service for many years.
- When used in a solar pumping system, directly connected to solar power, it will protect the pump from over-voltage and over-current conditions and will also provide current boosting in low sunshine conditions.
- The model LCB-G0 gives basic protection and can also be connected to a remote float switch at the reservoir to turn the pump on and off as required.
- The model LCB-G75 model has these facilities but is also equipped with sensors, wiring harness and internal circuitry to monitor water levels underground and react to level changes in the well and a manual on-off switch



FEATURES & BENEFITS



LCB-G0

- Operates on 24 VDC
- Increases daily water output up to 30%
- System starts pumping earlier in the morning
- Systems stops pumping later in the evening
- Protects pump from low or high voltage conditions
- Terminals for float switch
- 5 Amp Max



LCB-G75

Includes all features of LCB-G0 plus:

- Switch selectable for 12 VDC or 24 VDC
- Pump On / Off switch
- Water tight enclosure and cable inlets
- Includes water level monitor mode with probes and 90 m (300 ft.) cables
- 7 Amp Max
- Mounting bracket
- Terminals for float switch



SHURFLO® LINEAR CURRENT BOOSTER PUMP CONTROLLERS

FEATURES & BENEFITS

	Model LCB-G75	Model LCB-G0
Maximum input voltage	45VDC (Open circuit - max 2 panels in series)	45VDC (Open circuit - max 2 panels in series)
Start voltage of the PV pump system	18-32VDC - adjustable (set to 24 volts)	25VDC ± 2% adjustable
Shut-down voltage	28VDC	28VDC
Max. power consumption of the PV pump system	150 Watts	150 Watts
Max output current	7 Amps	5 Amps
Power consumption	25 mA	25 mA
Fuse (*)	10 Amps	10 Amps
Ambient temperature	-10° to +45°C	-10° to +45°C
Over-temperature shut-down	80°C	80°C
Short-circuit protection	Yes	Yes

(* Required for battery installation (not included))

Contact Information (EMEA):

Pentair Water Belgium B.V.B.A., Industriepark Wolfstee, Toekomstlaan 30, 2200 Herentals, Belgium
Phone: +32-14-259 911 - Fax: +32-14-259 975 - Email: shurflo.service@pentair.com



3545 HARBOR GATEWAY SOUTH, SUITE 103, COSTA MESA, CA 92626, (800) 854-3218 WWW.SHURFLO.COM

All Pentair trademarks and logos are owned by Pentair, Inc. All other brand or product names are trademarks or registered marks of their respective owners. Because we are continuously improving our products and services, Pentair reserves the right to change specifications without prior notice. Pentair is an equal opportunity employer.

MS-040-112 04/15 ©Pentair, Inc. All Rights Reserved.